

RADIO DSP 3 BANDS FM / AM / SW Bluetooth / USB / TF CARD PLAYER

OPERATING INSTRUCTIONS

OPERATION OF THE RADIO:

- 1. Turn on the ignition switch (11) as well as the volume control knob (11). Set it the appropriate volume.
- 2. Press (10), choose the MP3 or Radio, turn the switch (1) to select the program you want to capture.
- 3. Radio DSP 3 bands FM / AM / SW, please press (10) to choose many bands, or remove the telescopic antenna to get a better reception by changing its length and angle.
- 4. Receive AM using the internal magnetic antenna, and you can get the best reception by turning the direction of the radio.
- 5. Connect the USB (2) / TF (14), AUTOPRODUCTION, AUX support (1).
- 6. When you do not want to listen to the radio, turn off the ignition switch (11)

READER PLAYBACK OPERATING:

- 1.The default for Bluetooth status (Bluetooth device name BT-888)
- 2.With TF, U disc reader(Maximum support 32G),
- 3.No need to shift among U disc/TF, speaker automatically read the first input media device. If firs input TF, you need to take out TF card, then speaker can read Mp3 music file from U Disc.
- 4. Turn on the power switch(11).
- 5. Turn the volume control knob (11) adjust it to the appropriate volume.
- 6.Press the (4)for this PLAYBACK/PAUSE, Press the button (5) for the PREV, Press the button (6) for the NEXT.

1





Main parameter

3 BAND RADIO FM / AM / SW
BLUETOOTH /USB / TF CARD PLAYER
HIGH SENSITIVITY ANTENNA
RECHARGEABLE BATTERY
AC:220V/50Hz

DC: 5V

